



مشخصات فنی ژنراتور گاز سوز 50 کاوا

General characteristics	
Model name this package	Z24_Gas50
Engine made and model	NISSAN-Z24500
Fuel type	NG/CNG/LPG Gas
Number of cylinder	4 Cylinders
Alternator made and model	Standford 50KVA-40KW
Canopy	Rital IP42
Control panel model	COMAP-AMF25
Intelligent engine and generator speed control system	White energy

شرکت مهندسی و تولیدی دلارام تأمین بسامد



مشخصات فنی ژنراتور گاز سوز 50 کاوا

Intelligent water temperature and oil pressure control system	White energy
Dimensions (L*W*H mm)	2450*950*1100
Dry weight gensct (KG)	670
Technical Specifications of the Engine	
Engine Capacity	2400 CC
Maximum Engine Power	80HP
Maximum Engine Speed	4500RPM
The Power of the Engine is Running	51HP
Engine Running Speed	2700RPM
Maximum Engine Torque	160 (N.M) 2500 (RPM)

شرکت مهندسی و تولیدی دلارام تامین بسامد



مشخصات فنی ژنراتور گاز سوز 50 کاوا

Maximum Input Torque to the Generator	288 (N.M) 1500 (RPM)
Divice Gearbox Model	4W 81A
Conversion Ratio Power Transmission and Gearbox Speed	1.8
Engine Cooling System	Water
Oil Capacity	4
Operating Voltage	12VDC
Batteru and Capacity	1*74
Fuel Cons. Prime With 100% Load	LPG:3.5 kg/h - Cng 6 m3/h
Fuel Cons. Prime With 75% Load	LPG:2.5 kg/h - Cng 4.5 m3/h
Fuel Cons. Prime With 50% Load	LPG:1.8 kg/h - Cng 3 m3/h

شرکت مهندسی و تولیدی دلارام تامین بسامد



مشخصات فنی ژنراتور گاز سوز 50 کاوا

Device Generator Specifications	
Nominal Generator voltage	3PH-380VAC 1PH-220 VAC
Frequency	50HZ
Standby Rating	32KW 40VA
Prime Rating	28KW 35KVA
Standby Amper	1HP : 48A - 3PH : 145A
Prime Amper	1HP : 42A - 3PH : 126A
Time Prime	24H
Voltage Regulation	1
Insulation System	H

شرکت مهندسی و تولیدی دلارام تأمین بسامد



مشخصات فنی ژنراتور گاز سوز 50 کاوا

Protection	IP23
Rated Power Factor	0.8
Weight Comp Generator	240Kg

شرکت مهندسی و تولیدی دلارام تأمین بسامد